

Manufacturer:	Multi-amp
Model:	MS1A
Category:	Hipot / Ground Tester
Common Name:	Overload Relay / Circuit Breaker Test Set
Description:	<p>The Multi-Amp MS-1A Overload Relay and Circuit Breaker Test Set consists of a continuously variable autotransformer which supplies an output transformer, thus providing stepless control of the output current.</p> <p>Integral metering, timing, and control circuitry are included in the MS1A.</p> <p>Features:</p> <p>Rating: 0.6 kVA</p> <p>Input: 120 volts, 60 hertz, single phase</p> <p>Output: Continuously adjustable in four ranges to meet a variety of test circuit impedances: 0 - 140 volts at 4.5 amperes 0 - 24 volts at 25 amperes 0 - 6 volts at 100 amperes 0 - 3 volts at 200 amperes</p> <p>Ammeter: A large, easily read instrument with 3½ scale: Scales: 5 / 10 / 25 Ranges (switch selected): 0-2.5 / 5 / 10 / 25 / 50 / 100 / 250 / 500 amperes</p> <p>Timer: Measures elapsed time of the test from 0.1 second to 9999.9** seconds</p> <p>Housing: Molded plastic, high strength suitcase type enclosure with easy-to-carry handle. Storage space is provided for test leads</p>
Characteristics:	<p>INSTRUMENT TYPE -- Overload Relay / Circuit Breaker Test Set</p> <p>MAXIMUM CURRENT -- 200 ADC Max</p> <p>MAXIMUM DC VOLTAGE -- 140 VDC Max</p> <p>Meter Type -- Analog Display</p>
Length x Width x Height - Weight:	14" x 9" x 9" - 35 lbs.
Options:	
Accessories:	<p>MANUAL, OPERATION -- Qty 1</p> <p>TEST LEAD SET, MULTI-AMP MS-1A -- Qty 1</p>