

Product Description:

Boonton 56518 Peak Power Sensor, 500 MHz to 18.0 GHz, -40 to +20 dBm

Impedance:50 Ohm

Performance Characteristics of the 56518

Form Factor	Handheld
Minimum Frequency	0.5 GHz
Maximum Frequency	18 GHz
Minimum Power (dB)	-50 dBm
Maximum Power (dB)	20 dBm
Maximum Power (W)	200 mW
V/SWR, First Range	1.15: DC to 1GHz
V/SWR, Second Range	1.20: 1 to 6GHz
V/SWR, Third Range	1.28: 6 to 16GHz
V/SWR, Fourth Range	1.34: 16 to 18GHz
Connector type (main signal)	Type-N(m)